

Kwik Lite

Features

- INSTANT START
- LESS POWER MORE LIGHT
- POWER SAVING – 25%
- INCREASED LAMP LIFE
- WORKS FROM 90V - 140V AC
- FLICKER FREE

Technical Specifications

Model	KEPS 109 / 111
Lamp Wattage	1 x 11 CFL (Only 4 Pin CFL lamps)
Power Consumption	11.8 Watts
Mains Current	0.114
Power Factor	0.95
Ballast Loss	2W (Approx.)
Supply	110 AC
Functioning at low temp.	Minus 10 deg. C
Noise Level	NIL
Stroboscopic effect	Absent
Protection	Built-in fuse Short Circuit Protected
Starter on fitting	Not required
Temperature rise	8-10 deg. C above ambient
Operating Frequency	25 - 40KHz.
Dimensions	120x41x28 mm
Weight	Approx. 150 gms



Kwiklite Model No : KEPS 109/111

Clients for KEPS 109/111

- **Indian Railways**
- **Northeast Frontier Railway**
- **Southern Railways**
- **Central Railways**
- **BEML**
- **Kumar Electrical Industries**
- **Dr. Reddy's Laboratories**
- **Central Railways, Nagpur**
- **Dept. Of Space**
- **Indian Oil Corporation**
- **K.R Industries.,**
- **Texas Engg. & Contracting Co.,**
- **K-Lite Industries**
- **Electrical Radio Laboratory**
- **Integral Coach Factory**
- **Jessop and Co.**

..... and more

Contact us at : Premier Combines, Plot No.4 Mohammad Hussain Colony, Kolathur, Chennai – 600099.
Ph.No.: 044-26510195, Telefax No.:044-26510805 Visit us at: www.kwiklite.com Email: kwiklite@vsnl.com.