

# Kwik Lite

## Features

- INSTANT START
- LESS POWER MORE LIGHT
- POWER SAVING – 25%
- INCREASED LAMP LIFE
- WORKS FROM 120V - 280V



## Technical Specifications

Model	KEPS 326
Lamp Wattage	3 x 26 ( Only 4 Pin lamps to be used)
Power Consumption	82 Watts (app.)
Mains Current	0.34 Amps
Power Factor	0.99
Ballast Loss	3W (Approx.)
Supply	240V AC & DC
Functioning at low temp.	minus 10 deg. C
Noise Level	NIL
Stroboscopic effect	Absent
Protection	Built-in fuse Short Circuit Protected High Voltage Cut off
Starter on fitting	Not required
Temperature rise	10-15 deg. C above ambient
Crest Factor	< 1.7
THD	< 10%
Operating Frequency	greater than 25 KHz.
Dimensions	135x82x28 mm
Weight	Approx.300gms

**Kwiklite Model No : KEPS 326**

### Clients for KEPS 326

- **Baliga Lighting Equipment (I) Pvt. Ltd**
- **Bharat Earth Movers Ltd**
- **Dr. Reddy's Laboratories**
- **Dept. of Light Houses & Light Ships**
- **Dept. Of Space**
- **Taj Group of Hotels**
- **Mahindra Satyam**
- **Indian Oil Corporation**
- **K-Lite Industries**
- **Electrical Radio Laboratory**
- **Wheels India Ltd**

..... and more

Contact us at : Premier Combines, Plot No.4 Mohammad Hussain Colony, Kolathur, Chennai – 600099.  
Ph.No.: 044-26510195, Telefax No.:044-26510805 Visit us at: [www.kwiklite.com](http://www.kwiklite.com) Email: [kwiklite@vsnl.com](mailto:kwiklite@vsnl.com).