

# Kwik Lite

## Features

- LESS POWER MORE LIGHT
- POWER SAVING – 10%
- INCREASED LAMP LIFE
- WORKS FROM 140V - 280V
- CAN BE USED IN SV & MH



## Technical Specifications

<b>Model</b>	<b>KEPS HID 400W</b>
Lamp Wattage	400W
Power Consumption	410W
Mains Current	1.7 Amps (Max)
Power Factor	≥ 0.90
Ballast Loss	10W (Approx.)
Supply	240V AC & DC
Functioning at low temp.	minus 10 deg. C
Noise Level	NIL
Stroboscopic effect	Absent
Protection	Built-in fuse Auto restart Deactivated Lamp Sensing Abnormal Wattage Sensing Open Circuit Sensing
Ignitor	Not required
Power Factor Capacitor	Not required
Temperature rise	10-15 deg. C above ambient
Crest Factor	1.95 ± 10%
THD	< 30%
Operating Frequency	greater than 20 KHz.
Dimensions	190x135x75 mm
Weight	Approx. 1300 gms

Contact us at : Premier Combines, Plot No.4 Mohd. Hussain Colony, Kolathur, Chennai – 600099.  
Telefax No.:044-26510195 Visit us at: [www.kwiklite.com](http://www.kwiklite.com) Email: [kwiklite@vsnl.com](mailto:kwiklite@vsnl.com)