

# ***Kwik Lite***

## **Features**

- LESS POWER MORE LIGHT
- POWER SAVING – 15%
- INCREASED LAMP LIFE
- WORKS FROM 140V - 280V
- CAN BE USED IN LPSV & MH

## **Technical Specifications**

Model	KEPS HID 135
Lamp Wattage	35W
Power Consumption	37W
Mains Current	0.16 Amps
Power Factor	0.96
Ballast Loss	2W (Approx.)
Supply	240V AC & DC
Functioning at low temp.	minus 10 deg. C
Noise Level	NIL
Stroboscopic effect	Absent
Protection	Built-in fuse Open Circuit Sensing
Ignitor	Not required
Power Factor Capacitor	Not required
Auto restart	Provided
Temperature rise	8-10 deg. C above ambient
Crest Factor	< 1.95
THD	< 30%
Operating Frequency	greater than 20 KHz.
Dimensions	95x56x28 mm
Weight	Approx. 250 gms



**Kwiklite Model No : KEPS 135**

### **Clients for KEPS HID 135**

- **Baliga Lighting Equipment (I) Pvt. Ltd**
- **Bharat Earth Movers Ltd**
- **Dr. Reddy's Laboratories**
- **Oasis Luminaires P.Ltd**
- **Dept. Of Space**
- **Taj Group of Hotels**
- **Mahindra Satyam**
- **Indian Oil Corporation**
- **K-Lite Industries**
- **Wheels India Ltd**
- **Jessop and Co.**

*..... and more*

Contact us at : Premer Combines, Plot No.4 Mohammad Hussain Colony, Kolathur, Chennai – 600099.  
Ph.No.: 044-26510195, Telefax No.:044-26510805 Visit us at: [www.kwiklite.com](http://www.kwiklite.com) Email: [kwiklite@vsnl.com](mailto:kwiklite@vsnl.com).